

ACX-210

MINIATURE WIRELESS EXPANDER OF WIRED ZONES/OUTPUTS

The ACX–210 module makes it possible to use wired devices (detectors, sirens, etc.) in the ABAX 2/ABAX wireless system. It has 4 programmable zones with support for the NO and NC type wire detectors and EOL, 2 EOL configurations, as well as 4 programmable OC type wired outputs.

It is an expander of miniature type that requires little space for installation.

The device is supplied with voltage in the range of 4–24 V DC.

ACX-210 settings are configured and its firmware updated remotely. In the ABAX 2 system, two-way radio communication is encrypted using is AES encrypted.

- adding wired devices to the ABAX 2 or ABAX system
- compatible with:
 - ABAX 2 system controllers (ACU-220 and ACU-280) and ARU-200 radio signal repeater
 - ABAX system controllers (ACU-120, ACU-270, ACU-250 and ACU-100 (min. version 4.04), INTEGRA 128-WRL control panel and ARU-100 radio signal repeater - the required version of the device firmware should be checked in its description on the website
- range of radio communication in the open area:
 - o in ABAX 2: up to 2000 m (with ACU-220) / up to 1400 m (with ACU-280)
 - o in ABAX: up to 500 m
- 4 programmable zones support for wired detectors in NO, NC, EOL, 2EOL/NO and 2EOL/NC configurations
- 4 programmable OC type outputs
- remote configuration and update of the firmware
- · compact dimensions
- power supply: 4-24 V DC

TECHNICAL DATA

-10°C+55°C
424 V DC
30 mA
35 mA
10 g
93±3%
868,0 ÷ 868,6 MHz
21 x 41 x 13 mm
EN 50130-4, EN 50130-5, EN 50131-1, EN 50131-3, EN 50131-5-3
Grade 2
up to 500 m
up to 500 m
up to 2000 m
up to 1400 m
50 mA / 12 V DC

