

AMBER 2E

PIR MOTION DETECTOR

AMBER is a motion detector using dual element PIR sensor. Digital detection algorithm and temperature compensation algorithm are used for reliable operation in a wide range of ambient temperatures as well as high immunity to false alarms. The detector is provided with built-in EOL resistors for easy installation and connection to the alarm system. The device has a red LED indicating violation of the supervised area as well as tamper protection against opening the enclosure. AMBER is characterized by low power consumption (< 3 mA).

The main task of the detector is to detect violations in the protected area. However, it can also be used to implement the building automation functions. When the alarm system is not armed, the detector can control turning on the lights, opening or closing the door, etc. Compact size is one of AMBER advantages: it is one of the smallest motion detectors offered by SATEL, and that's why it is eagerly chosen by the users.

- build-in EOL resistors
- digital signal processing
- temperature compensation
- sensitivity adjustment

TECHNICAL DATA

Supply voltage	12 V DC
Detected target velocity	0,3...3 m/s
Operating temperature range	-30...+55 °C
Recommended mounting height	2,4 m
Standby mode current consumption	3 mA
Max. current consumption	3 mA
Weight	35 g
Maximum humidity	93 ±3%
Dimensions	48,5 x 66 x 36 mm
Environmental class according to EN50130-5	II
Alarm signaling time	2 s
EOL resistors	2 x 1,1 kΩ
Warm-up period	ok. 120 s



The actual appearance of the products may differ from the presented images. Product descriptions are provided in the web service for information purposes only.